

REPOWER SELECTION GUIDE

1st, the current models are highlighted, so first, pick the model with the HP closest to the old model.

2nd, match the mounting centers for ease of installation.

3rd, make sure it fits.

4th, look at the overall engine data and make the final selection based on the best match.

1				2		3	4			
MODEL	MFG	HP	# CYL	MTG CENTERS	REAR MTG CTR	OVERALL LENGTH	RPM	CID	MAX TORQUE	@ RPM
7A One	W	6.4	1	12/14		25.1	3400	17.7	11.3	2590
P10/W10	W	10	1	14.5			3000	29.4	20	2000
W10 Two	W	10	2	15		25	3600	27.5	18	2200
11A One	W	10.7	1	18.9		23.7	3000	32	20.4	2170
M2-12	U	11	2	14.5/16		23	3600	26	19.5	2600
12C Two	W	12	2	14.5		25	3000	38.8	20	2200
12D Two	W	12	2	14.5		25.6	3000	38.8	23	2300
W13	W	13.5	2	14.5/16/18		26.3	3000	27	25	2500
4-60	W	15	4	13/15/18	18	37.5	2500	58	36	1800
M15	U	15	2	11.5		25.6	3000	31	21.9	2000
W18	W	18	3	14.5/16		28.4	3300	48	30	2400
M18	U	18	2	11.5/16		24.8	3200	34.8	25.6	2175
M3-20	U	18	3	11.5/16		25.9	3600	39	28.5	2500
P20	W	20	2	15.5		32.3	3000	58.8	40	1500
M3-20B	U	20	3	11.5/14.5/16		26.4	3600	43.8	33	2500
M25	U	21	3	11.5/16		28.5	3200	52	40	1850
L25	W	22	4	20/22.75		35.25	2400	97.6	58	2400
RD60	W	22	4	11.5			3000	50		
W21	W	22	3	14.5/16		28.38	3000	60	42	2000
M25XP	U	23	3	11.5/16		27.5	3200	57	43.8	1850
M25XPB	U	26	3	11.5/16		28.4	3000	61.2	47	2440
M4-30	U	25	4	11.5/16		29.1	3600	52	39	2600
30B Three	W	27	3	16		28.8	3600	58	43	2200
30C Three	W	25	3	16		29.3	3600	58	43	2200
W27	W	30	3	14.5/16		32.6	3000	80	55	2600
M30	U	30	3	16		32.5	2800	68	52	1600
W30	W	30	4	16/18	18	41	3000	91	58	1800
M35	U	30	4	11.5/16		31.8	3200	75	56	1800
35C Three	W	29	3	14.5/16		29.6	3600	80.4	47	2260
35D Three	W	31	3	14.5/16/18.5		29.6	3000	80.4	59	1940
35E Three	W	28	3	14.6/16/18.5		30.6	3000	80.4	49	2000
M40	U	32	4	16		35.5	2800	91	68	1600
35B Three	W	32	3	14.5/16		30.1	3600	68	41	2300
W33	W	33	4	16/18		34.6	3000	91	67	2100
38B Four	W	37	4	14.5/16		33.77	3600	79.6	53	2400
W40	W	40	4	16/18		40.5	3000	107	80	2250
44A Four	W	40	4	14.5/16/18.5		33.4	3600	107.2	76	1920
44B Four	W	44	4	14.5/16/18.5		34.9	3000	107.3	77	2480
W50	W	41	4	18			3200	110	85	2000
M50B	U	42	4	16		36	2800	113.3	97	1690
42B Four	W	42	4	14.5/16		33.78	3600	91	56	2500
M50	U	44	4	16		36	3000	115	87.9	1600
44C	W	38	4	14.6/16/18.5		34	3000	107.3	70	2000

REPOWER SELECTION GUIDE

MODEL	MFG	HP	# CYL	MTG CENTERS	REAR MTG CTR	OVERALL LENGTH	RPM	CID	MAX TORQUE	@ RPM
W46	W	46	4	16/18/20/22.5		36.72	3000	127	100	2250
W52	W	52	4	18		39	3000	135	93	2500
55A Four	W	55	4	16/18.5		35.2	3600	133.2	93	1920
55B Four	W	55	4	16/18.6		35.2	3000	133.2	110	1500
55C Four	W	55	4	16/18.5		35.4	3000	133	110	1500
55D	W	48	4	16/18.5		35.4	2600	133	105	1600
W58	W	58	4	18/20/22.5		48.5	3000	154	117.9	2200
W60	W	60	4	20/22.5		48.5	3000	154	130	2000
63B Four		63	4	18		38.75	3600	134.8	93	2900
63C Four		63	4	18.5		38.8	3600	134.8	95	2280
63D Four	W	61	4	18.5		38.8	3600	134.8	95	2280
64A Four	W	64	4	18.5//20/22.5		38.8	2600	182	132	1970
65A Four	W	65	4	20/22.5		40.9	2800	202.5		
65B Four	W	66	4	20/22.5		40.9	2600	202.5	163	1400
W70	W	70	4	22.5		38.62	3000	182	148	1800
71C Four	W	71	4	18.5/20/22.5		39.3	3600	154	118	1950
W80	W	75	4	20/22.5		51.5	2600	230	170	1700
80-N4	W	80	4	22.5		47.2	2500	262	210	1500
82B Four	W	82	4	22.5		38.8	3600	182	146	1890
90A Four	W	90	4	22.5		39.3	3600	210.8	168	1670
W100	W	100	6	22.5		57	3000	247	195	1800
108C Six	W	108	6	22.5		54.4	3600	247.2	192	1830
110-T4	W	110	4	22.5		47.2	2400	262	296	1240
W120	W	115	6	20/22.5			2800	346		
120-N6	W	120	6			56.4	2500	396	298	1500
5411	U	SEE M15								
5424	U	SEE M30								
5432	U	SEE M40								
5444	U	SEE M50								
M50A	U	SEE M50								
4-91	W	SEE W30								
4-107	W	SEE W40								
4-108	W	SEE W40								
4-154	W	SEE W58 or W60								

* Specifications are subject to change without notice